## Product data sheet

Specifications



## NEMA Motor Starter, Type S, replacement coil, 380 VAC 50 Hz, NEMA Size 00, 0 and 1 starters and 8903SM lighting

3104140057



() Discontinued on: Nov 20, 2023

# Product availability: Non-Stock - Not normally stocked in distribution facility

#### Main

Product Or Component Type	Coil
Accessory / Separate Part Destination	Class 8502 type SA (series A)/SB/SC contactor Class 8536 type SA (series A)/SB/SC starter Class 8903 type SM lighting contactor

#### Complementary

j		
Nema Size	1 00 0	
[Ue] Rated Operational Voltage	380 V AC 50 Hz	
Inrush Power In Va	232 VA	
Average Consumption	26 VA	
Height	2.15 in (54.7 mm)	
Width	3.21 in (81.5 mm)	
Depth	1.90 in (48.3 mm)	

#### Ordering and shipping details

Category	US1CP1018079
Discount Schedule	CP10
Gtin	785901620389
Returnability	No
Country Of Origin	MX

#### **Packing Units**

U	
Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Height	3.23 in (8.2 cm)
Package 1 Width	1.89 in (4.8 cm)
Package 1 Length	2.17 in (5.5 cm)
Package 1 Weight	7.36 oz (208.652 g)

Price is "List Price" and may be subject to a trade discount - check with your local distributor or retailer for actual price.

### **Contractual warranty**

Warranty

18 months

#### **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

**Eu Rohs Directive** 

Not applicable, out of EU RoHS legal scope