Product data sheet

Specifications





NEMA Control Relay, timing relay, 2 NO, one minute on delay, 220/240 VAC 50/60 Hz coil

8501XO20XTE1V03

Discontinued on: Jul 1, 2020



Main

| Range | 8501X | |
|-----------------|-------------------|--|
| Relay Type | Timing | |
| Product | Relay | |
| Current Rating | 10 A AC 5 A DC | |
| Number Of Poles | 2P | |
| Voltage Rating | 600 V AC | |

Complementary

| Coil Voltage | 220 V AC 50 Hz 240 V AC 60 Hz |
|-----------------------|--|
| | |
| Coil Voltage Limints | Operational 0.851.1 Uc AC 50/60 Hz |
| Breaking Current | 6 A 120 V AC inductive control circuit UL 508 3 A 240 V AC inductive control circuit UL 508 |
| | 1.5 A 480 V AC inductive control circuit UL 508 |
| | 1.2 A 600 V AC inductive control circuit UL 508 |
| | 10 A <= 600 V AC resistive control circuit UL 508 |
| | 1.1 A 125 V DC inductive control circuit UL 508 |
| | 0.55 A 250 V DC inductive control circuit UL 508 |
| | 0.2 A 301600 V DC inductive control circuit UL 508 |
| | 4 A 125 V DC resistive control circuit UL 508 |
| | 0.8 A 250 V DC resistive control circuit UL 508 |
| Making Current | 60 A 120 V AC inductive control circuit UL 508 |
| | 30 A 240 V AC inductive control circuit UL 508 |
| | 15 A 480 V AC inductive control circuit UL 508 |
| | 12 A 600 V AC inductive control circuit UL 508 |
| | 10 A <= 600 V AC resistive control circuit UL 508 |
| | 1.1 A 125 V DC inductive control circuit UL 508 |
| | 0.55 A 250 V DC inductive control circuit UL 508 |
| | 0.2 A 301600 V DC inductive control circuit UL 508 |
| | 4 A 125 V DC inductive control circuit UL 508 |
| | 0.8 A 250 V DC resistive control circuit UL 508 |
| Time Delay Type | On-delay |
| Time Delay Time | 0.260 s |
| Coil Inrush Power | 148 VA 60 Hz |
| | 143 VA 50 Hz |
| Coil Sealed Power | 23 VA 60 Hz |
| | 25 VA 50 Hz |
| Device Operating Time | 15 ms - pick-up |
| | 16 ms - drop-out |
| Contact Configuration | 2 NO 2 standard contact cartridges |
| | |

Price is "List Price" and may be subject to a trade discount - check with your local distributor or retailer for actual price.

| Electrical Connection | Screw clamp terminals |
|-----------------------------|--|
| Wire Gauge | AWG 18AWG 12 copper |
| Terminal Tightening Torque | Control circuit 9.0312.04 lbf.in (1.021.36 N.m) screw terminal |
| Mounting Type | Panel |
| Operating Temperature Range | -40160 °F (-4071 °C) |
| Height | 3.5 in (88.90 mm) |
| Width | 2.23 in (56.64 mm) |
| Depth | 6.55 in (166.37 mm) |

Environment

Product Certifications

CSA LR60905 class 3211 03 UL listed file E78403 CCN NKCR

Ordering and shipping details

| Category | 21158-8501 XO (AC) |
|-------------------|--------------------|
| Discount Schedule | CP2 |
| Returnability | No |
| Country Of Origin | MX |

Packing Units

| Unit Type Of Package 1 | PCE |
|------------------------------|-----|
| Number Of Units In Package 1 | 1 |

Contractual warranty

Warranty

18 months

Sustainability Screen

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >



Transparency RoHS/REACh

Well-being performance

Mercury Free

Rohs Exemption Information Yes

Certifications & Standards

| Reach Regulation | REACh Declaration |
|---------------------------|--|
| Eu Rohs Directive | Pro-active compliance (Product out of EU RoHS legal scope) |
| China Rohs Regulation | China RoHS declaration |
| Environmental Disclosure | Product Environmental Profile |
| California Proposition 65 | WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov |