

# COMBO STARTER 600VAC 540A NEMA

8538SHG12V02S

! To be discontinued on: Sep 30, 2024

Product availability: Non-Stock - Not normally stocked in distribution facility

### Main

| Product              | Combination Starter      |
|----------------------|--------------------------|
| Туре                 | S                        |
| Control Circuit Type | Separate control circuit |

## Complementary

| ,                       |  |
|-------------------------|--|
| Control Circuit Voltage | 110 V AC 50 Hz<br>120 V AC 60 Hz                     |
| Starter Type            | Non reversing  |
| Number Of Poles         | 3P   |
| Horsepower Rating       | 400 hp 460 V AC, 3 phase<br>400 hp 575 V AC, 3 phase |
| Maximum Voltage Rating  | 600 V AC   |
| Control Units           | No control units                                     |
| Pilot Light             | No indicator   |
| Auxiliary Contacts      | Without  |
| Thermal Overload Type   | Melting alloy 3                                      |
| Disconnect Type         | Fusible disconnect switch H, 600 A                   |
| Nema Size               | 6  |

#### **Environment**

Enclosure Type NEMA 1 painted sheet steel with external reset

## Ordering and shipping details

| Category          | 21216 - 8538,39 SH,SJ(NOT S*R,T,W) |
|-------------------|------------------------------------|
| Discount Schedule | CP1                                |
| Returnability     | No                                 |
| Country Of Origin | MX                                 |

## **Packing Units**

| Unit Type Of Package 1       | PCE                        |
|------------------------------|----------------------------|
| Number Of Units In Package 1 | 1                          |
| Package 1 Weight             | 425.00 lb(US) (192.777 kg) |

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

# **Contractual warranty**

Warranty

18 months

## **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

| Eu Rohs Directive         | Not compliant   |
|---------------------------|---|
| China Rohs Regulation     | China RoHS declaration  |
|                           | Product out of China RoHS scope. Substance declaration for your information.  |
| California Proposition 65 | WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov |