

! To be discontinued

NEMA Combination Starter, Type S, Mag Guard circuit breaker, Size 6, 540A, 3 phase, 600 VAC coil, NEMA 12

8539SHA54V07

! To be discontinued on: Sep 30, 2024

Product availability: Non-Stock - Not normally stocked in distribution facility

#### Main

Product	Combination Starter
Туре	S
Control Circuit Type	Common control circuit

## Complementary

550 V AC 50 Hz
600 V AC 60 Hz
Non reversing
3P
125 hp 200 V AC, 3 phase
300 hp 460 V AC, 3 phase
125.15 hp 230 V AC, 3 phase
350.4 hp 575 V AC, 3 phase
600 V AC
No control units
No indicator
Without
Melting alloy 3
Mag-Gard circuit breaker

#### **Environment**

Enclosure Type	NEMA 12 painted sheet steel with external reset
Nema Size	6

### Ordering and shipping details

Category	21216 - 8538,39 SH,SJ(NOT S*R,T,W)
Discount Schedule	CP1
Returnability	No
Country Of Origin	MX

## **Packing Units**

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Unit Type Of Package 1	PCE
Number Of Units In Package 1	1
Package 1 Weight	440.00 lb(US) (199.581 kg)

# **Contractual warranty**

Warranty 18 months

# **Sustainability**

**Green Premium<sup>TM</sup> label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO<sub>2</sub> products.

**Guide to assessing product sustainability** is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

**Eu Rohs Directive** 

Not compliant