

! To be discontinued

NEMA Combination Starter, Type S, LJL electronic motor circuit protector, Size 6, 540A, 3 phase, 208 VAC coil, NEMA 12

8539SHA55V08

! To be discontinued on: Sep 30, 2024

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Combination Starter		
Туре	S		
Control Circuit Type	Common control circuit		

Complementary

Control Circuit Voltage	208 V AC 60 Hz				
Starter Type	Non reversing				
Number Of Poles	3P				
Horsepower Rating	125150 hp 200 V AC, 3 phase 125150 hp 230 V AC, 3 phase 250350 hp 460 V AC, 3 phase 300400 hp 575 V AC, 3 phase				
Maximum Voltage Rating	600 V AC				
Control Units	No control units				
Pilot Light	No indicator				
Auxiliary Contacts	Without				
Thermal Overload Type	Melting alloy 3				
Disconnect Type	Mag-Gard circuit breaker				

Environment

Enclosure Type	NEMA 12 painted sheet steel with external reset
Nema Size	6

Ordering and shipping details

Category	21216 - 8538,39 SH,SJ(NOT S*R,T,W)				
Discount Schedule	CP1				
Returnability	No				
Country Of Origin	MX				

Packing Units

<u> </u>			
Unit Type Of Package 1	PCE		

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

 Number Of Units In Package 1
 1

 Package 1 Weight
 440.00 lb(US) (199.581 kg)

Contractual warranty

Warranty 18 months

Sustainability

Green PremiumTM label is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >

Eu Rohs Directive

Not compliant