



s

# REVERSING COMBO STARTER 600VAC 18ANEM

8739SBW51V02S

#### Main

Device Short Name

## Complementary

| Depth                               | 11.4 in (289.56 mm)                               |
|-------------------------------------|---|
| Device Mounting                     | Surface   |
| Height                              | 27 in (685.80 mm)                                 |
| Maximum Horse Power Rating          | 0.250.34 hp 200/230 V AC<br>0.251 hp 460/575 V AC |
| Motor Starter Type                  | Reversing   |
| Nema Size                           | 0   |
| Number Of Poles                     | 3   |
| Number Of Thermal Units<br>Required | 3   |
| Product Destination                 | Circuit breaker GJL36003M01                       |
| Width                               | 25.25 in (641.35 mm)                              |

#### **Environment**

| Nema Degree Of Protection | NEMA 4X           |
|---------------------------|-------------------|
| Product Certifications    | NEMA<br>UL Listed |

## Ordering and shipping details

| Category          | 21297-8738,39 W/STAINLESS ENCLOS |
|-------------------|----------------------------------|
| Discount Schedule | CP1                              |
| Returnability     | No                               |

## **Packing Units**

| Unit Type Of Package 1       | PCE                      |
|------------------------------|--------------------------|
| Number Of Units In Package 1 | 1                        |
| Package 1 Weight             | 57.00 lb(US) (25.855 kg) |

#### **Contractual warranty**

Warranty 18 months

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.