

LRA36400U53X

PowerPact L I-Line Circuit Breaker, Micrologic5.3E, 400A, 3P, 600V, 100kA

Product availability : Non-Stock - Not normally stocked in distribution facility



Price* : 14,618.00 USD



Main

Product or component type	Circuit breaker
Range of product	PowerPact L
Trip Unit Type	Electronic energy Micrologic 5.3 E LSI
Interrupt Code	R

Complementary

Protection technology	Current limiter
Line Rated Current	400 A
Number of Poles	3P
Interrupt Rating	200 kA at 240 V AC 200 kA at 480 V AC 100 kA at 600 V AC
System Voltage	600 V AC
Continuous current rating	80 %
Mounting mode	I-Line
Electrical connection	I-Line connection line Lugs load
Wire Size	AWG 3/0...500 kcmil (aluminium/copper) 2(cable(s))
Terminal Type	AL600LF52K3
I-Line Phase Connection	ABC
Height	14.7 in
Width	5.94 in
Depth	6.61 in
Tightening torque	4.4...50 N.m 95...240 mm ² AWG 3/0...500 kcmil 4.4...50 N.m AWG 3/0...500 kcmil

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environment

Product certifications	CCC CE CSA UL listed NMX
------------------------	--------------------------------------

Ordering and shipping details

Category	01111 - L HIGH INTERRUPT I-LINE BREAKER/SW
Discount Schedule	DE2
Nbr. of units in pkg.	1
Package weight(Lbs)	14
Returnability	Y
Country of origin	US

Offer Sustainability

RoHS (date code: YYWW)	Compliant Schneider Electric declaration of conformity
REACH	Reference not containing SVHC above the threshold Reference not containing SVHC above the threshold
California proposition 65	WARNING: This product can expose you to chemicals including:
----- Substance 1	DINP, which is known to the State of California to cause cancer, and
----- Substance 2	DIDP, which is known to the State of California to cause Birth Defects or other reproductive harm.
----- More information	For more information go to www.p65warnings.ca.gov

Contractual warranty

Warranty period	18 months
-----------------	-----------